



## MISSION M12 XHP70

### — Operating Instruction —

#### Features

- Cree XHP70 LED outputs, up to 5,000 hours service time
- Maximum output 3200 lumens.
- Micro orange-peel reflector
- Maximum beam distance 525 meters
- Powered by 2pc of 26650 Li-ion rechargeable battery
- 233mm (length) \* 66mm (head diameter) \* 30mm (body diameter)
- Weight 334g
- Reverse polarity protection
- Memory function
- Anti-slip and sweat wicking knurling
- Dual switch controls brightness levels and flashing modes separately
- Made from aircraft-grade aluminum
- Mil-Spec Type III hard-anodized finish
- Toughened ultra-clear glass lens with blue coating on both sides
- Waterproof to IPX-8 standard, underwater 2 meters.

#### Technical Parameters

ANSI/NEMA F11	TURBO	HIGH	MID	LOW
Light Output	3200 Lumens	2750 Lumens	1860 Lumens	590 Lumens
Runtime	—	2h	5h30min	30h
Beam Distance	525m			
Impact Resistance	1.5m			
Waterproof	Waterproof up to one hundred meters			
Specifications	233mm(Length)*66mm(head)*30mm(Body)			

Above referential results are tested by using 2pcs MAXTOCH 26650 Li-ion battery (3.7V/3400mAh). The result may vary when adopting different batteries or in different environment.

#### Operation Instruction

##### Master switch For ON/OFF and output selections

Long press and hold the master switch when the light is off to activate Boost mode quickly.

Release the switch and the light goes off.

Single press the master switch to turn the flashlight ON/OFF, then long press the switch to shift four output levels in order of Boost Low Mid High.

In flash mode, single press the main switch could enter into general mode. It starts at the last-used brightness level.

##### Auxiliary switch For flash modes only

Single press to enter/quit flash mode.

With the light on, single long press the auxiliary switch to cycle through Strobe Heartbeat Signal SOS modes.

In general mode, single click the auxiliary switch could enter flash mode. It starts at the last-used flash mode.

#### Battery Replacement

Take off the tail cap. Then insert 2pcs of 26650 battery with the positive terminal towards the head. After loading the batteries, screw the tail cap on with all of the threads in proper alignment.

#### Warning

MISSION M12 is a high-intensity lighting device capable of causing eye damage to the user or others. Avoid shining the flashlight directly into anyone's eyes please.

#### Usage and Maintenance

- Disassembling the sealed head can cause damage to the light and will void the warranty.
- High quality battery is recommended. If the light will not be used for an extended period, remove the battery, or the light could be damaged by electrolyte leakage or battery explosion.

Long-term use can result in O-ring wear. To maintain a proper water seal, replace the ring with an approved spare.

- When the head part or tail cap can't be turned smoothly, apply silicone grease on threads please.

#### Optional Accessories

MAXTOCH offers various accessories to meet different requirements. You could learn more from our online store <http://www.aliexpress.com/store/314381>

#### Warranty

1 years warranty -MAXTOCH offers free warranty work iff the problem is caused by normal usage within 1 years after receipt.

Lifetime warranty - For the life of your light, repairs will be made with no labor charges and as long as parts are available from MAXTOCH. You will be charged for the parts needed to repair your light.

#### Following situations are excluded from warranty

- Damage caused by improper disassemblment, modification and improper usage is excluded from warranty.
- Battery is excluded from warranty. If the battery doesn't work upon receipt, it could be replaced.
- Accessories come along with flashlight such as lanyards, bag, o-ring, etc..) are not covered by the warranty.

For the latest information on MAXTOCH® products and services, please send an email to [service@maxtoch.cn](mailto:service@maxtoch.cn).

All images, text and statements specified herein this user manual are for reference purpose only. Should any discrepancy occurs between this manual and information specified on [www.MAXTOCH.com](http://www.MAXTOCH.com), EST Group Co., Ltd reserves the rights to interpret and amend the content of this document at any time without prior notice.

EST Group Co., Ltd.

Tel- +86-571-81022450

Email- [service@maxtoch.cn](mailto:service@maxtoch.cn)

Website- [www.maxtoch.com](http://www.maxtoch.com)