

# NICRON®

Safe & Reliable Portable Lighting Tools



## B62 (18650x1)

Max brightness 950 Lumens

Aoneng Lighting Co., Ltd.

Thank you for choosing NICRON flashlight, please double check the manual before using!

### Product Features

- Fashion patent appearance design, good touch feeling, handstand design.
- High grade air-craft aluminum body with military type III hard anodizing coating.
- Using CREE XPL HD V5 LED, 50000 hours life time.
- High volume, safe and reliable 18650 li-ion rechargeable battery, short, over and dis-over charging resistant.
- Micro-USB cable charge can be compatible with standard mobile phone charger.
- Import electrical component with High efficiency constant current circuit design to extend run time. Overcharge and over discharge PCB design to protect the battery life.
- Smart heat-sink releasing system to keep body in safe temperature.
- High-end body metal switch easy to adjust mode, go straight in strobe mode any time when emergency
- Aluminum reflector with high lighting effect.
- Switch life time 50000 times, IPX 7, 1m water resistant.

### Parameter Description

1. Function setting as below table:

FL1 STANDARD	Super low	Low	Mid	High	Super high	Blinking	SOS
brightness (LM)	15	45	120	330	950	950	950
run time (hrs)	60	30	8	7	5	N/A	N/A
beam distance				170meter			
max intensity				7200 cd			
drop testing				1.0 meter			
water proof	IPX 7, 1 meter water proof						

Above datum tested base on ANSI FL 2009 standard with the 2600mAh li-ion battery, maybe vary depending on different environment.

2. Bulb: GREE XPL HD V5 white light LED.
3. Using 1pc safety 2600mAh 18650 LI-ION rechargeable battery.
4. Voltage range: 3.0~4.2V.
5. Material: air-craft aluminum.
6. Weight: 82g, exclude the battery.
7. Size: 128 x 29 x 23.5mm.
8. Normal usage temperature: -20°C ~ 50°C.

### Operating Instructions

1. On-Off : push the switch 0.5s to control the light into on- off. Slight push the button to change mode: super low-low-middle-high-super high –super low etc. Push the switch more than 1.2 s anytime, it will turn to hide model: Strobe- SOS.
2. Charging: put rechargeable battery in correct direction into torch, the main light have slight blinking when charging, stop blinking when full.
3. When low power the main light also will be blinking remind user to charge the light in time.

### Use and Maintenance

- Please do not open the fixed head parts, otherwise, has risk to damage the light without warranty.
- Please use good quality battery, take out the battery when you are going to power off for a long time, since the battery maybe damaged or bomb by itself if you put it for a very long time.
- Please often to clean the current contact pin and surface to ensure light up normally, especially when you find out the light flash a little bit by itself.
- Please close the concealed charge and reverse charge module if you don't need when using and store.

Below is the normal cannot work and flash issues:

- Caution 1: battery run out  
solution: please use new battery in correct direction.
- Caution 2: thread or PCB with dirty thing  
solution: clean the PCB or thread by Alcohol Swabs if still not work,  
please contact +86 757 2232 8481

### Caution

1. Please don't light up the flashlight fact to your eyes directly, it will dangerous to damage your eyes or eye slight.
2. The products only design to use 18650 size battery.
3. Do not throw the 18650 batter into fire or water, please put it in correct polarity when charging.
4. We suggest charging the battery each 3 month at least to protect the battery life if you plan to storage the product for a long time.
5. Please keep the battery far away from children, if eating by mistake, please go hospital at once.

### Warranty Terms

1. Within 15 days of purchase, any defective lights will be offered free replacement by NICRON distributors unconditionally. except for damages caused by misuse, insert batteries in wrong way or batteries weeping.
2. Within 24 months from the date of purchase. NICRON offers free repair after service, except for damages caused by misuse, insert batteries in wrong way or batteries weeping.(battery and accessories only 0.5 year)
3. Limited lifetime warranty. NICRON will still provide with warranty service. Labor is free but we will charge for parts. The total repair fee is assessed according to the cost of the replaced materials. Freight should be paid by customers.
4. More details about warranty service, please contact local distributors or dealers.



Aoneng Lighting Co., Ltd.

No. 2, North Shunyuan Road, Shunde Industrial Park, Wusha, Daliang, Shunde, Foshan, Guangdong, China.

post code: 528333

Официальный представитель на территории РК и СНГ - интернет-магазин KupiFonar.kz

8 (727) 2496770

email: info@kupifonar.kz

web: https://www.kupifonar.kz

